

# HID-Basic Gearbox system for SON (India)

## BSN 150 X261

Impregnated electromagnetic ballasts of copper and steel construction for use in combination with an external ignitor for High-Pressure Sodium Vapor (SON) lamps

### Warnings and Safety

- Ballasts are only suitable for use with integrated luminaires

### Product data

General Information	
Application Code	150 X261
Lamp Type	SON/MHN-TD/CDM
Number of Lamps	1 piece/unit
Operating and Electrical	
Input Voltage	240 V
Input Frequency	50 Hz
Mains Voltage Performance (AC)	240+6%--8%
Mains Voltage Safety (AC)	240-10%--+10%
Input Current with PF Correction	0.83 A
Input Current without PF Correction	1.80 A
Power Factor with PF Compensation	0.85
Power Factor without PF Compensation (Nom)	0.40
Power Losses (Nom)	21 W


Wiring	
Connector Type	Screw
System characteristics	
Rated Ballast-Lamp Power	150 W
Temperature	
T-Winding (Max)	130 °C
Delta-T Normal Conditions	75 °C
Approval and Application	
Energy Efficiency Index	Not specified
Approval Marks	CE marking
Product Data	
Full product code	871150088460200
Order product name	BSN 150 X261

## HID-Basic Gearbox system for SON (India)

EAN/UPC - Product	8711500884602
Order code	913702253212
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	4

Material Nr. (12NC)	913702253212
Net Weight (Piece)	2.055 kg

### Dimensional drawing



Product	D1	C1	A1	A2	B1
BSN 150 X261	6.3 mm	64.0 mm	132.0 mm	116.0 mm	75.0 mm

BSN 150 X261

