



Uni DMX controls and accessories

ZXP399 DMX controller 12V 8port

Uni DMX controls and accessories, Black

The ZXP399 DMX Controls and Wiring Accessories are to be used with our architectural and facade lighting luminaires (UniFlood C, M and G, UniStrip G4, UniEdge, UniDot G2, UniString and UniBar). DMX Controls include main controller, stand-alone controller, sub-controllers, DMX amplifier and DMX addressing device. Main Controller: Industrial computer that can control up to 6000 DMX universes. Stand-alone Controller: Fits for medium applications with up to 700 DMX universes. Wiring accessories include leader and jumper cables with male and female IP67 connectors and end-caps. Addressing Device: Hand-held device that can write DMX addresses to a whole run on-site within minutes. DMX Amplifier: Compact, IP65 and low power repeater that can amplify the DMX signal for up 100 meters.

Product data

| | | | | |
|-------------------------------------|-------------------------|---------------------------------|---------------------------------|----------|
| Operating and Electrical | | Net Weight (Piece) | | 1.550 kg |
| Input Voltage | 12 DC V | Approval and Application | | |
| Protection class IEC | Safety class III | CE mark | Yes | |
| Mechanical and Housing | | Product Data | | |
| Overall length | 228 mm | Order product name | ZXP399 DMX controller 12V 8port | |
| Overall width | 197 mm | Full product name | ZXP399 DMX controller 12V 8port | |
| Overall height | 66 mm | Full product code | 871951494733700 | |
| Dimensions (Height x Width x Depth) | 66 x 197 x 228 mm | Order code | 911401779642 | |
| Material | Aluminum | Material Nr. (12NC) | 911401779642 | |
| Ingress protection code | IP20 [Finger-protected] | Numerator - Quantity Per Pack | 1 | |
| Accessory color | Black | | | |

Uni DMX controls and accessories

| | |
|---------------------------------|---------------|
| EAN/UPC - Product/Case | 8719514947337 |
| Numerator - Packs per outer box | 1 |
| EAN/UPC - Case | 8719514947337 |

Dimensional drawing

